



JBC CP-2QF 230V Micro Tweezers Soldering Station Instruction Manual

[Home](#) » [JBC](#) » JBC CP-2QF 230V Micro Tweezers Soldering Station Instruction Manual 

Contents

- 1 JBC CP-2QF 230V Micro Tweezers Soldering Station
- 2 Packing List
- 3 Features and Connections
- 4 Tip Cleaner
- 5 Changing Cartridges
- 6 Compatible Cartridges
- 7 Operation
- 8 Control Process
- 9 Parameters
- 10 USB Connector
- 11 Maintenance
- 12 Safety
- 13 Specifications
- 14 Warranty
- 15 Documents / Resources
- 16 Related Posts

JBC

JBC CP-2QF 230V Micro Tweezers Soldering Station



This manual corresponds to the following references:

- CP-9QF (100V)
- CP-1QF (120V)
- CP-2QF (230V)

Packing List

The following items are included:



Control Unit 1 unit



Adjustable Micro Tweezers 1 unit
Ref. AM120-A




Power Cord 1 unit
Ref. 0024092 (100V)
0023715 (120V)
0023714 (230V)



Brass Wool 1 unit
Ref. CL6210





Sponge 1 unit
Ref. S0354






Manual 1 unit
Ref. 0026946

Features and Connections



Adjustable Stand

Adjust the tool stand to suit your work position.



Cable Collector (Ref. CC1001)

Place the cable on the collector so that the working area is free of cable.

Tip Cleaner

Select the option to suit your needs and improve the thermal transfer of the tip.

Splashguard

Ref. 0017576

When using the brass wool, it prevents splashing of solder particles.

Antisplash Membrane




Ref. 0017574

Prevents splashing and keeps the work area clean.

Brass Wool

Ref. CL6210

Very effective cleaning method. Leaves a small layer of solder on the tip preventing oxidation between cleaning and rewetting.



If the tip is very dirty, JBC recommends first cleaning it with the wiper to remove excess solder.


Wiper

Ref. CL0160


A temperature resistant receptacle for removing excess solder by gently tapping or wiping.

Removing the Splashguard


1. Unlock the splashguard.



2. Lift off.



More cleaning options (not supplied):




Inox Wool
Ref. CL6205
Stronger cleaning method than brass wool.




Metal Brush
Ref. CL6220
When used carefully, it provides a more thorough cleaning.

Wiper
Ref. CL0160




Tapping:
Tap gently to remove excess solder.



Wiping:
Use the slots to remove remaining particles.


Sponge
Ref. S0354



The softest cleaning method. Keep the sponge damp with distilled water when working to avoid tip wear.


Changing Cartridges

1. Removing




Place the cartridges in the extractor and pull to remove the cartridge.

2. Positioning



Place the tweezers on top of the new cartridge and press down slightly.

3. Inserting




Use the holes for fixing the cartridges*.

Important


It is essential to insert the cartridges as far as the mark for a proper connection.

4. Rotational Cartridge Alignment



Slightly turn the wheels to align the cartridges as required.


5. Vertical Cartridge Alignment




Close the tweezers and the rear wheel allows the cartridges to be equally aligned in vertical direction.

Compatible Cartridges


The CDP stations work with C120 cartridges and AM120 Adjustable Micro Tweezers. Find the model that best suits



Conical Bent



Blade



Chisel Bent

Operation


The JBC Exclusive Heating System

This revolutionary technology is able to recover tip temperature extremely quickly.

This allows the user to work at a lower temperature.


As a result, tip life increases by 5.

1. Work




When the tool is lifted from the stand the tip will heat up to the selected temperature.

2. Sleep




When the tool is in the stand, the temperature falls to the preset sleep temperature.

3. Hibernation




After longer periods of inactivity, the power is cut off and the tool cools down to room temperature.



- Change temperature (from 90 to 450°C)
 - ^ v Steps ± 5
 - < > Steps ± 50



- Through menu settings:
- Change Sleep temperature
 - Set Sleep delay (from 0 to 9 min or no Sleep)




- Through menu settings:
- Change Hibernation delay (from 0 to 35 min)

Through menu settings:

- Select temperature levels
- Fix one temperature


Control Process

Work Screen



Menu Screen

Default PIN: 0105




Troubleshooting

Station troubleshooting available on the product page at www.jbctools.com.


Parameters

Be careful when using these parameters as they may reduce the tip life if not used properly Please follow the recommended guidelines:

Station Settings

Parameter Description	Recommendations	Warnings
Temperature Unit Celsius (°C) or Fahrenheit (°F)	N/a	
Maximum Temperature Set the maximum temperature to work with. Max. temp by default is 400°C (750°F). This is considered high enough to work with most lead-free applications.	The station temperature range is 90-450°C (190-840°F). Change the temperature limits when working with less common applications such as low / high melting point soldering (HMP) or plastics (e. g. riveting).	 In most cases, working with temperatures over 400°C (750°F) can damage the PCB and its components. Even in short time periods of tip contact with the soldering joint, the flux may not work properly and could seriously reduce tip life. If the solder joint requires more power (e.g. multilayered or high dissipation boards), JBC strongly recommends using other aids like preheaters.
Minimum Temperature Set the minimum temperature to work with. Min. temp. by default is 200°C (392°F). This is considered to be a proper starting point for leaded applications.		
Metronome This activates a beep sound. Frequencies vary from 1 to 50 seconds.	Useful for setting a work rate in repetitive jobs. The beep lets you know the length of time the tip must be in contact with the soldering joint.	N/a
Beep Enable/disable the beep sound of the keypad.	N/a	N/a
QST Enable/disable QST.	N/a	N/a
Pin Enable/disable pin prompt.	N/a	N/a
Change Pin Change the default security PIN number (0105).	The PIN must be entered every time a parameter is changed.	N/a

Tool Settings

Parameter Description	Recommendations	Warnings
<p>Fix One Temperature Fix a value within the temperature range of the station (90-450°C/190-840°F).</p>	<p>Ideal for soldering more than one component at a specific temperature. The station will reject any attempt to change the temperature.</p>	N/a
<p>Temperature Levels Set Similar to "Fix one temp" parameter. In this case, the user can set up to 3 values for different power requirements.</p>	<p>This allows a quick change between 3 different temperatures. Set them according to the allowed values for your soldering applications.</p>	N/a
<p>Sleep Delay Set the time that the tool will remain at the selected temperature when in the stand before entering sleep mode. The tip temperature will then drop to the Sleep temperature.</p>	<p>Because our tools reach the working temperature from the default Sleep mode in only a few seconds, this parameter is preset to 0 min. Once the tool is returned to the stand the temperature will automatically drop to the sleep temperature, extending tip life and avoiding oxidation. Retinning the tip before placing the tool in the stand will protect the tip and extend its life.</p>	<p> Setting these parameters to higher values will unnecessarily accelerate oxidation and shorten tip life especially when working with temperatures up to 450°C (840°F).</p>
<p>Sleep Temperature This is the set temperature the tip reaches when returned to the stand.</p>	<p>The sleep temperatures are set to achieve a balance between preventing oxidation and reaching the working temperature in a few seconds.</p>	

Parameter Description	Recommendations	Warnings
<p>Hibernation Delay Set the time the tool will remain at Sleep temperature before entering the Hibernation mode. At this time, the power supply is cut off and the tip remains at room temperature.</p>	<p>This function completely protects the tip from oxidation during long periods of inactivity while the tool is in the stand. Retinning the tip before placing the tool in the stand also helps prevent oxidation and extends the life of the tip.</p>	<p>⚠ Increasing the default value will accelerate oxidation and shorten the tip life.</p>
<p>Temp Adjustment It provides a more precise adjustment between the selected temperature and the actual one.</p>	<p>Set values within $\pm 50^{\circ}\text{C}$ ($\pm 90^{\circ}\text{F}$) to achieve zero error. JBC strongly recommends the use of TID-A or TIA-A Thermometers to obtain precise readings.</p>	<p>⚠ When the user changes the cartridge type, the parameter should be reset to $0^{\circ}\text{C}/\text{F}$ or to the value needed for this cartridge. E.g. If a correction of $+20^{\circ}\text{C}$ ($+36^{\circ}\text{F}$) is set for a thick cartridge and then the user changes to a thinner one without resetting the temperature adjustment, he would be working at a higher temperature than needed for this thinner cartridge, which does not need any temperature adjustment.</p>

USB Connector

Download the latest software from our website to update your soldering station.

JBC Updater

www.jbctools.com/software.html


Update the station software via USB connection:



JBC Web Manager




www.jbctools.com/manager.html

Manage and monitor as many stations as your PC can handle by using the JBC Web Manager. You can export data to another PC.



Maintenance

Before carrying out maintenance, always switch the device off and disconnect it from the mains. Allow the equipment to cool down.



- Clean the station screen with a glass cleaner or a damp cloth.
- Use a damp cloth to clean the casing and the tool. Alcohol can only be used to clean the metal parts.
- Periodically check that the metal parts of the tool and stand are clean so that the station can detect the tool status.
- Maintain tip surface clean and tinned prior to storage in order to avoid tip oxidation. Rusty and dirty surfaces reduce heat transfer to the solder joint.
- Periodically check all cables and tubes.
- Replace any defective or damaged pieces. Only use original JBC spare parts.
- Replace a blown fuse as follows:
 1. Pull off the fuse holder and remove the fuse. If necessary use a tool to lever it off.
 2. Insert the new fuse into the fuse holder and return it to the station.
- When this warning appears on the main screen Earthing Fuse must be replaced
- -Repairs should only be performed by a JBC-authorized technical service.

Safety

It is imperative to follow safety guidelines to prevent electric shock, injury, fire or explosion.

- Do not use the units for any purpose other than soldering or rework. Incorrect use may cause fire. The power cord must be plugged into approved bases. Be sure that it is properly grounded before use. When unplugging it, hold the plug, not the wire.
- Do not work on electrically live parts.
- The tool should be placed in the stand when not in use in order to activate the sleep mode. The soldering tip, the metal part of the tool and the stand may still be hot even when the station is turned off. Handle with care, including when adjusting the stand position.
- Do not leave the appliance unattended when it is on.
- Do not cover the ventilation grills. Heat can cause inflammable products to ignite.
- Avoid flux coming into contact with skin or eyes to prevent irritation.
- Be careful with the fumes produced when soldering.
- Keep your workplace clean and tidy. Wear appropriate protection glasses and gloves when working to avoid personal harm.
- Utmost care must be taken with liquid tin waste which can cause burns.
- The appliance can be used by children over the age of eight and also persons with reduced physical, sensory or mental capabilities or lack of experience provided that they have been given adequate
- Supervision or instruction concerning use of the appliance and understand the hazards involved. Children must not play with the appliance.
- Maintenance must not be carried out by children unless supervised.

Specifications

CP-9QF 100V 50/60Hz. Input fuse: T2A. Output: 23,5V.

CP-1QF 120V 50/60Hz. Input fuse: T2A. Output: 23,5V.

CP-2QF 230V 50/60Hz. Input fuse: T1A. Output: 23,5V.

- Output Peak Power CP-F: 80W
 - Temperature Range: 90 – 450 °C / 190 – 840 °F
 - Idle Temp. Stability (still air): $\pm 1.5^{\circ}\text{C}$ / $\pm 3^{\circ}\text{F}$ (Meets and exceed IPC J-STD-001)
 - Temp. Accuracy: $\pm 3\%$ (Using reference cartridge)
 - Temp. Adjustment: $\pm 50^{\circ}\text{C}$ / $\pm 90^{\circ}\text{F}$ (Through station menu setting)
 - Tip to Ground Voltage/Resistance: Meets and exceed ANSI/ESD S20.20-2014 IPC J-STD-001F
 - Earthing Fuse: F 1.25A
 - Connections: USB connector station-P RJ12 connector
 - Ambient Operating Temp.: 10 – 50 °C / 50 – 122 °F
 - Control Unit Dimensions / Weight: 170 x 176 x 145 mm / 2.8 kg (L x W x H) 6.7 x 6.9 x 5.7 in / 6.17 lb
 - Total Net Weight: 3kg / 6.61 lb
 - Total Package Dimensions / Weight: 234 x 234 x 258 mm / 3.15 kg (L x W x H) 9.2 x 9.2 x 10.2 in / 6.94 lb
- Complies with CE standards ESD protected housing “skin effect”

Warranty


JBC's 2 year warranty covers this equipment against all manufacturing defects, including the replacement of defective parts and labour. Warranty does not cover product wear or misuse. In order for the warranty to be valid, equipment must be returned, postage paid, to the dealer where it was purchased.

Get 1 extra year JBC warranty by registering here: <https://www.jbctools.com/productregistration/> within 30 days of purchase.

DISPOSAL

This product should not be thrown in the garbage. In accordance with the European directive 2012/19/EU, electronic equipment at the end of its life must be collected and returned to an authorized recycling facility. www.jbctools.com

Documents / Resources

 <p>JBC www.jbctools.com INSTRUCTION MANUAL</p> <p>CDP Micro Tweezers Soldering Station</p>	<p>JBC CP-2QF 230V Micro Tweezers Soldering Station [pdf] Instruction Manual CP-9QF 100V, CP-1QF 120V, CP-2QF 230V, Micro Tweezers Soldering Station, CP-2QF 230V Micro Tweezers Soldering Station, Tweezers Soldering Station, Soldering Station, Station</p>
------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

[Manuals+](#)